


SS60401

Solid-state Relay Module



Description


The SS60401 solid-state switch module has been designed specifically to replace the CP Clare electro-mechanical CUPV60401 relay where it is used in low current switching applications.

The SS60401 is designed around the CP Clare PAA110 Dual Pole OptoMOS® Relay - a 400V, 150mA, 22ohm, 2-Form-A solid-state device. This device provides high peak load voltage handling capability and improved peak load current handling.

Advantages

- Lower cost
- No large M.O.Q. / M.O.V.
- Environmentally friendly (no mercury)
- Lower power consumption
- High reliability
- Arc free
- No EMI/RFI generation

Pin Configuration



Absolute Maximum Ratings (@ 25°C)

| Parameter | Min | Typ. | Max | Units |
|-------------------------------------|------|------|------------------|------------------|
| Input Voltage Maximum | - | - | 6 | V |
| Reverse Input Voltage | - | - | 6 | V |
| Output Power Dissipation | - | - | 500 ¹ | mW |
| Isolation Voltage (Input to Output) | 3750 | - | - | V _{RMS} |
| Operational Temperature | -40 | - | +85 | °C |
| Storage Temperature | -40 | - | +125 | °C |
| Soldering Temperature | - | - | +260 | °C |

¹ Derate Linearly 6.67mW / °C

Electrical Characteristics


| Parameter | Conditions | Symbol | Min | Typ | Max | Units |
|--------------------------------------|--|-------------------|------|------|------|------------------|
| Output Characteristics @ 25°C | | | | | | |
| Load Voltage (Continuous) | - | V _L | - | 250 | - | V |
| Load Voltage (Peak) | - | V _L | - | - | 400 | V |
| Load Current* (Continuous) | - | I _L | - | - | 150 | mA |
| Load Current (Peak) | 10mS | I _{LPK} | - | - | 400 | mA |
| On-Resistance | I _L =150mA | R _{ON} | - | 15 | 22 | Ω |
| Off-State Leakage Current | V _L =400V | I _{LEAK} | - | - | 1 | μA |
| Switching Speeds | | | | | | |
| Turn-On | I _F =5mA, V _L =10V | T _{ON} | - | - | 1 | μS |
| Turn-Off | I _F =5mA, V _L =10V | T _{OFF} | - | - | 0.25 | μS |
| Output Capacitance | 50V; f=1MHZ | C _{OUT} | - | 25 | - | pF |
| Input Characteristics @ 25°C | | | | | | |
| Input Control Voltage | I _L =150mA | V _I | 2.7 | - | 5.5 | V |
| Input Dropout Voltage | - | V _I | 0.6 | 1 | - | V |
| Input Current | V _I =5V | I _F | 12 | 14.5 | 18 | mA |
| Reverse Input Voltage | - | V _R | - | - | 5 | V |
| Reverse Input Current | V _R =5V | I _R | - | - | 10 | μA |
| Input to Output Capacitance | - | C _{I/O} | - | 3 | - | pF |
| Input to Output Isolation | - | V _{I/O} | 3750 | - | - | V _{RMS} |

* Note: - as both poles are operated simultaneously, load current must be derated so as not to exceed package power dissipation.

Performance Data

For performance data graphs, please refer to CP Clare data sheet DS-PAA110-R3.

Mechanical Data



Ordering Information

| DAtEK Part Number | Description |
|-------------------|--|
| SS60401 | CP Clare CUPV60401 solid-state replacement |

Price & Delivery*

| DAtEK Part Number | 1 - 99 | 100 - 499 | 500 - 999 | 1000+ |
|-------------------|--------|-----------|-----------|-------|
| SS60401 | | | P.O.A. | |

*small quantities (< 50 pieces) ex-stock, larger quantities 2-3 weeks

Contact Information

DAtEK Services
20 Lewisvale Court
Musselburgh
East Lothian
EH21 7HR

Tel: 0131 665 4677
Fax: 0131 665 3677
Email: sales@datekservices.com